# UVM001-0101U1-RN1

Precaution

This product, UVC LED assembly, emits deep ultraviolet light.


Do not irradiate the body directly because UVC has a strong influence on cells. Do not look directly at light. / Avoid direct exposure to skin.

Please be careful of handling of UVC and conduct the driving confirmation based on your judgment.

CITIZEN ELECTRONICS CO., LTD. shall not be liable for any personal or property damage due to deep ultraviolet light.



DATA SHEET	02208
1. Scope of Application This datasheet is applied to UVM001-0101U1-RN1	
<sup>2. Part code</sup> <u>UVM 001</u> - <u>01</u> <u>01</u> <u>01</u> <u>1</u> <u>01</u> <u>01</u> <u>01</u> <u>01</u>	
[1] Product name	
[2] Die count in series 1	
[3] Die count in parallel 1	
[4] UVC package U1	
[5] Luminous Intensity Distribution Reflector Narrow 1 $\times$ 1 $\times$ 1 As for irradiation range, please refer to Effective Irradiation Range of 4. Performance (2)	)
■ Features ■	
Purpose : disinfection	
<ul> <li>LED : UVC LED Peak wavelength 260~270nm ※2</li> <li>※2 Wavelength range of LED to be mounted should be the specification value of the LED manufacturer at Tc=25℃ 500mA</li> </ul>	
Outline Drawing: 42.0×27.0×10.0mm	
Structure : High-heat dissipation structure on aluminum base	
Performance of dustproof and waterproof : equivalent to IP54	
Compliant with RoHS2.0 Directive and halogen free	
$\Delta 2$	
$\bigtriangleup 1$	
Mark         Number of mark         Date         Details of change         Drawr           CITIZEN ELECTRONICS CO         LTD	ו by



Ref\_CE-0888P-202208

3/12

#### 4. Performance

#### (1) Absolute Maximum Rating

Parameter	Symbol	Maximum Rating Value	Unit	
Input Power	Pi	4.0	W	*1
Forward Current	I <sub>F</sub>	500	mA	*1
Reverse Voltage	V <sub>R</sub>	-5	V	
Operating Temperature Range (Ambient temperature)	T <sub>op</sub>	-10 ~ +45	°	
Storage Temperature Range	T <sub>st</sub>	-25 ~ +75	°C	
Case temperature	T <sub>c</sub>	70	°	*2
Tightening Torque	-	0.6	N∙m	

\*1 Input power, forward current and case temperatures are values for use within the range of the derating curve described in this data sheet.

\*2 As for measurement point of case temperature, refer to 3. Outline drawing

#### (2) UVC LED Assembly Characteristics (Electrical and physical characteristics) Tc=25 $^{\circ}$ $\times 1 \times 2$


Parameter	Symbol	Condition	MIN	TYP	MAX	Unit
Forward Voltage	V <sub>F</sub>	I <sub>F</sub> =250mA	4.4	-	7.3	V
Central radiant intensity %3	—	I <sub>F</sub> =250mA	0.023	(0.081)	-	mW/cm <sup>2</sup>
Ambient irradiance %4	_	I <sub>F</sub> =250mA	0.015	(0.040)	-	mW/cm <sup>2</sup>


%1 The measurement distance is 22 cm.


Distance from UVC LED to the top surface of the glass is 0.78cm

%2 Measurement tolerances: Forward Voltage ±3%, Illuminance ±10%

×3 ×4 For Central radiant intensity and ambient irradiance, please refer to below figures







#### 6. Reliability

(1) Details of the Tests

Test item	Test conditions	Test hours
Continuous Operation	I <sub>F</sub> =250mA Ta=25℃ Tc=35℃	500 hours
High Temperature and High Humidity Operation Test	I <sub>F</sub> =250mA Ta=45℃ Tc=55℃ 95%	500 hours
Low Temperature Storage Test	Ta=-25℃	500 hours
High Temperature Storage Test	Ta=75℃	500 hours
High Temperature and High Humidity Storage Test	Ta=45℃ 95%	500 hours
Temperature Cycle Test	Ta=-25℃(30min)~75℃(30min) one cycles	100 cycles

Note) Ta means ambient temperature.

(2) Judgment Criteria of Failure for Reliability Test


(Ta=25℃)

Measuring	Item	Symbol	Measuring Condition	Judgement Criteria for Failure
Forward V	oltage	V <sub>F</sub>	I <sub>F</sub> =250mA	>U X 1.1
Irradia	nce	-	I <sub>F</sub> =250mA	<s 0.50<="" td="" x=""></s>

U : means the upper limit of the specified characteristics. S : means the initial value

Note) Measurement shall be taken between 2 hours and 48 hours, having returned the test pieces to the normal ambient conditions after the completion of each test.

I				
∆5		·'		
∆4		í'		
∆3		·'		
△2		·'		
$\triangle 1$		·'		
Mark	Number of mark	Date	Details of change	Drawn by



	DATA SHEET				
	UATA SHEET	8/12			
8. Prec	autions				
(	1) Handling precautions				
	$\cdot$ This product is a product that emits deep ultraviolet rays (UVC).				
	UVC has a strong influence on cells, so direct exposure to the body is dangerous.				
	$\cdot$ JISZ8812 defines the allowable amount of ultraviolet rays, which is 4.6 mJ / cm <sup>2</sup> (8 hours a day)				
	for 260 nm and 3mJ / cm <sup>2</sup> (8 hours a day) for 270 nm.				
	Do not look at UVC lighting directly because there is a risk of eye pain or visual impairment.				
	Irradiating the skin directly with UVC light may cause skin irritation.				
	Please take measures such as using protective glasses or gloves to prevent direct exposure of				
	ultraviolet rays to the human body.				
	Also, pay attention not only to the direct light itself but also to reflected light.				
	• Ultraviolet rays are also irradiated outside the effective irradiance range described in 4. Performance	е.			
	$\cdot$ Ultraviolet rays deteriorate wallpaper or resin products, etc. Also, if you irradiate at a short distance	, the color			
	of such may change rapidly. Please be careful regarding deterioration and discoloration of the object	t exposed to light.			
	Diante are consitive to UV light. Depending on the type of plant, the leaves may will be die				
	• Plants are sensitive to UV light. Depending on the type of plant, the leaves may wilt or die.				
	$\cdot$ We are not liable for any personal or property damage caused to you or a third party due to UV exp	osure.			
	Please do not touch the glass area because it is an optical product and such contact impacts				
	on the function, performance and reliability of the product.	h - h - t			
	Do not touch the glass area or its surroundings during or immediately after irradiation as they may	be not.			
	$\cdot$ Please do not apply stress to the product by swinging or pulling the lead.				
	• Do not add excessive shock by a dropping and so on. It may cause a malfunction or an unexpected	accident.			
	$\cdot$ Covering or sealing the product may cause heat to build up inside and it may cause a fire or malfun	ction.			
	$\cdot$ Disassembling or modifying the product may cause a part to drop off, fire, electric shock, or injury.				
	• If you connect or disconnect the power supply line or operate the product with wet hands, you may	receive			
	an electric shock.	a ab a al (			
	• If you notice a strange odor or smoke, cease operation it immediately. It may cause a fire or electri	C SNOCK.			
	• Do not use for any purpose other than sterilization.				
∆5					
∆4					
∆3					
∆2					
riangle 1					
Mark	Number of mark         Date         Details of change	Drawn by			
	CITIZEN ELECTRONICS CO., LTD.				

<u>9/12</u>

#### (2) Precautions regarding product fixing

- It is recommended to fix the UVC LED assembly with M3 screws. Please attach the UVC LED assembly by temporarily tightening the left and right screws and then conducting final tightening of the screws to prevent the application of an excessive stress or strain on them.
- Conditions for fixing the product to a heatsink such as screw tightening torque should be optimized with specifications of the heatsink to be fixed.

• Burrs that are generated by roughness of the surface to be attached, concave-convex shape and cutting process, etc. may weaken the thermal coupling with the heatsink and increase thermal resistance. Please ensure that both thermal coupling and mechanical coupling are achieved by confirming the condition of the joint of the surface to be attached and evaluating Tc temperature.

• When fastening the product, please apply TIM (Thermal Interface Material: material for heat dissipation) to the whole rear face of the LED package to reduce thermal resistance.

- If you use grease-like TIM, please apply it evenly to the whole rear face of aluminum substrate of the UVC LED assembly.
- If you use a TIM sheet, make sure that aluminum substrate does not warp when the screws are tightened to fasten the product.
- When using the product while it is adhered to something or while connected to another component constituting one body,make sure to confirm that the quality of the product is not affected by way of an appropriate method.
- (3) Countermeasure against static electricity
  - Handling of this product requires countermeasures against static electricity because it is a semiconductor product. Please take adequate measures to prevent any static electricity being produced such as by wearing of a wristband or antistatic gloves.
  - Every manufacturing facility concerned with the product (plant, equipment, machine, carrier machine and conveyance unit) should be grounded to prevent the product from being electric-charged.
  - After assembling the UVC LED assembly into your final product(s), it is recommended to check whether the assembled UVC LED assembly have been damaged by static electricity (electrical leak phenomenon) or not.

△5				
∆4				
∆3				
△2				
riangle 1				
Mark	Number of mark	Date	Details of change	Drawn by

<u>10/12</u>

- (4) Regarding heat radiation design
  - In order for the LED to emit light efficiently, appropriate heat radiation based on heat radiation design is necessary. Please develop a heat radiation design for the LED so that the generated heat does not exceed the absolute maximum.
  - Temperature rise of the product depends on the thermal resistance within and outside the package, loss of power, and the temperature of the environment, so get the condition of operation considering the heat radiation design specification and the surrounding environment's temperature.
- (5) LED driving conditions
  - It is recommended to drive the UVC LED assembly by using constant current.
  - Please ensure no excessive current, excessive voltage or excessive reverse voltage electrical transients is applied to the UVC LED assembly when turning ON or OFF the UVC LED assembly.
  - Ensure the power supply system of this product is separate from lighting equipment and other equipment.
- (6) Operating environment and storage
  - This product is not designed for usage under the following conditions.
     If the product is used or may be used in the following environments, you must take appropriate measures and evaluate the effect before use.
     Places where the product is or may:
    - had the still and the still an
    - $\boldsymbol{\cdot}$  be directly or indirectly wet with rain or splash
    - $\cdot$  be damaged by sea breeze or salt
    - be exposed to corrosive gas (such as  $Cl_2$ ,  $H_2S$ ,  $NH_3$ , SOx, NOx, etc.)
    - be exposed to dust, fluid or oil
  - Do not use or store the product under conditions where chlorine, sulfur, acid or alkaline gas, or salt which is compressed or condensed is present, or where factors that generate corrosion exist.
  - Please store the product at ambient temperature between 5 to  $40^{\circ}$ C and at RH between 20 to 70%. Please keep the product away from direct sunlight and dust.

∆5				
∆4				
∆3				
△2				
riangle 1				
Mark	Number of mark	Date	Details of change	Drawn by
				• • • • •

			DATA SHEET		Ref_CE-0888P-202208	
					11/12	
9. Otł	ner precautions					
	・Warranty pe	riod is half a ye	ar from the day we delivered the product (under the	e storage conditior	ns we specify.)	
	<ul> <li>We guarantee the delivered products themselves within the reliability test result items and the conditions.</li> <li>In cases where the product is used in situations outside the conditions described in this delivery specification and such causes an accident or damage, we will not be held liable.</li> </ul>					
	actual devic in practical u as safety and • If any defect	e. Please confi ise at your con d reliability and	ngs of this product are also applied when assembling m service life and quality of the product in the assem pany. Also, please sufficiently verify conformance to assurance of performance of the final product on yo the warranty period, do not disassemble or disman ts instruction.	nbled device and the standards suc our own responsibi	h lity.	
			nd, we will take measures with mutual consultation, d to CE, we will deliver a replacement product in prir		at the defective	
	• Our warrant	y does not cov	r situations where this product undergoes secondary	y fabrication such	as change in shape.	
	・Do not rever	se-engineer th	e product including disassembling or analysis without	t our approval.		
	<ul> <li>This product is intended to be used for general electronic equipment such as general lighting, home appliances, and information-communication equipment. It is not desinged or manufactured to be used for special application (eg. automobiles, trains, ships, airplanes, spaceships, submarine repeaters, atomic energy control systems, combustion equipment, life-support systems, safety devices). We will not guarantee any application suitability for goods like those described above that require special quality and reliability.</li> <li>In cases where the product is used in special applications and it causes an extensive property damage, threatens human life or damages the human body, we will not be held liable.</li> </ul>					
	or loss that a • When desing of a single p	arise from the o ging as a set w	v disadvantage, damage or cause of legal action, or a se or nonuse of technical information or data of this ere safety is important, make sure to consider the ir ne whole set, and ensure safety with a fail-safe design ction device.	specification.	unction	
∆5						
∆4						
∆3						
△2						
		D-t-				
Mark	Number of mark	Date			Drawn by	

DATA SHEET	Ref_CE-0888P-202208
	12/12
<ul> <li>This technical information and data is provided for users as is, and Citizen Electronics Co., Ltd.</li> <li>does not guarantee that it is free from errors or defect in technical information and data, or this technical information and data conform to special applications, or this technical information and data does not infringe any rights of the user or third parties other than the user, or any other contents</li> </ul>	
Citizen Electronics Co., Ltd. reserves a right to modify technical information and data wi	ithout notice.
<ul> <li>Customers in Japan are requested to ensure compliance with domestic laws and regulat as the Foreign Exchange Law when exporting this product, and as for customers in cour outside of Japan, please ensure compliance with the applicable laws and regulations of and take appropriate action(s) such as obtaining an export license.</li> </ul>	ntries or areas
<ul> <li>Please do not use or supply this product for any weapons of mass destruction (WMD) of military purposes.</li> </ul>	or for any other
<ul> <li>This data sheet constitutes the entire agreement between Citizen Electronics and your company a to the matters regarding the product, and any prior agreement that was made before the receipt data sheet and that is not specified in the data sheet will cease to have effect.</li> </ul>	
<ul> <li>The contents of this document are not guaranteed because the specification and appear product may change without notice for improvement. Please exchange formal specificat prior to use for mass production.</li> </ul>	
Information in this document (text, photos or images) is subject to copyright and is protected It is prohibited by law to reproduce or reprint the information without approval of Citizen Elec except for "reproduction for private use" or for "quotes."	
Image: Constraint of the system       Image: Constraint of the system         Image: Constraint of the system       Image: Constraint of the system         Image: Constraint of the system       Image: Constraint of the system         Image: Constraint of the system       Image: Constraint of the system         Image: Constraint of the system       Image: Constraint of the system         Image: Constraint of the system       Image: Constraint of the system         Image: Constraint of the system       Image: Constraint of the system         Image: Constraint of the system       Image: Constraint of the system         Image: Constraint of the system       Image: Constraint of the system         Image: Constraint of the system       Image: Constraint of the system         Image: Constraint of the system       Image: Constraint of the system         Image: Constraint of the system       Image: Constraint of the system         Image: Constraint of the system       Image: Constraint of the system         Image: Constraint of the system       Image: Constraint of the system         Image: Constraint of the system       Image: Constraint of the system         Image: Constraint of the system       Image: Constraint of the system         Image: Constraint of the system       Image: Constraint of the system         Image: Constraint of the system       Image: Constraint of the system	
△5	
<u>∆3</u> <u>∆2</u>	
$\land 1$	

Details of change CITIZEN ELECTRONICS CO., LTD.

Mark

Number of mark

Date

Drawn by